

MRI Conductivity

Category

Healthcare Tools

State-of-the-art algorithms for MRI phase-based electrical conductivity mapping

Learn more

Notice:

An applicant for an academic licence must provide the full name of their relevant organisation otherwise the application will be rejected.



Quantitative Conductivity Mapping (QCM) is a non-invasive technique that calculates the high-frequency tissue electrical conductivity (σ) from the phase (φ_0) of the MRI signal¹. QCM has a range of potential clinical applications including measuring sodium levels², and distinguishing between different types of brain glioma³.

a) Laplacian-based methods

Most QCM methods are based on the following differential equation¹, valid in regions with slowly varying σ :

$$\sigma = (\mu_0 \omega)^{-1} \nabla^2 \varphi_0 \quad [1]$$

where μ_0 is the vacuum permeability, ω is the proton Larmor frequency, and ∇^2 is the Laplacian operator. Applying a finite-difference approximation of ∇^2 severely amplifies the noise⁴ (Figure 1a), which is why most current methods fit a 3D quadratic function within a kernel (Figure 1b) around each voxel and calculate the Laplacian of these fitted functions^{5,6}. This 3D quadratic fit is usually either i) weighted by the magnitude values within the kernel⁵ (Figure 1c) or ii) restricted to voxels from the same tissue type⁷ (Figure 1d) to avoid artifacts at the conductivity boundaries where Eq. 1 is not applicable.

While these are the most commonly used methods for QCM, there is a lack of readily available implementations that could be used as a standard. Here, we have implemented a MATLAB function that performs QCM by quadratic fitting within an ellipsoidal kernel of user-defined dimensions and with options for i) magnitude- or ii) segmentation-based edge preservation. Moreover, i) and ii) can be used in combination (Figure 1e), which is a new approach that shows promise for outperforming all the other techniques (Figure 1).

b) Surface-integral-based methods

Eq. 1 can also be formulated as a surface integral⁸ that has previously been suggested to be more noise-robust than the differential form⁹:

$$\sigma = (\mu_0 \omega V)^{-1} \int_S \varphi_0 \quad [2]$$

where S is a closed surface of some kernel with volume V . To solve this equation, only the first derivatives of φ_0 need to be calculated which induces less noise amplification than estimating the Laplacian. φ_0 can be calculated using the 3D quadratic fitting approach described above. Since Eq. 2 is also not valid at the conductivity boundaries, i) magnitude-, and/or ii)

segmentation-based restrictions can be applied to both kernels (one for calculating and another one for calculating the surface integral).

Though we have recently shown that the integral-based methods are more accurate than the differential-based approaches (Figure 1), very few studies have previously applied these (using small kernels only without i) or ii)) possibly because the surface integral is tricky to implement. Here, we have implemented a MATLAB function that performs QCM by solving Eq. 2 with options for i), ii), or i) and ii) combined. These methods are all entirely new.

By disseminating this software, we hope to accelerate QCM research and its translation into a wide range of clinical applications.




Figure 1: Optimised conductivity maps calculated using 10 different methods in an anthropomorphic brain phantom (top) and an in-vivo brain image (bottom). Mean absolute errors in the brain are also shown for the phantom. White rectangles highlight the superior performance of the integral-based methods.

1. Katscher, Ulrich, and Cornelius AT van den Berg. "Electric properties tomography: biochemical, physical and technical background, evaluation and clinical applications." *NMR in Biomedicine* 30.8 (2017): e3729.
2. Liao, Yupeng, et al. "Correlation of quantitative conductivity mapping and total tissue sodium concentration at 3T/4T." *Magnetic resonance in medicine* 82.4 (2019): 1518-1526.
3. Tha, Khin Khin, et al. "Noninvasive electrical conductivity measurement by MRI: a test of its validity and the electrical conductivity characteristics of glioma." *European radiology* 28.1 (2018): 348-355.
4. Karsa, Anita, and Shmueli, Karin. "Simultaneous Noise Suppression and Edge Preservation in Phase-based MRI Conductivity Mapping." *Proceedings of the Annual Meeting of the ESMRMB*. (2020).
5. Lee, Joonsung, Jaewook Shin, and Dong Hyun Kim. "MR based conductivity imaging using multiple receiver coils." *Magnetic resonance in medicine* 76.2 (2016): 530-539.

6. Shin, Jaewook, et al. "Initial study on in vivo conductivity mapping of breast cancer using MRI." *Journal of Magnetic Resonance Imaging* 42.2 (2015): 371-378.

7. Katscher, Ulrich, et al. "Estimation of breast tumor conductivity using parabolic phase fitting." *Adapting MR in a Changing World: ISMRM 20th Annual Meeting, Melbourne, Australia, 5-11 May 2012*.

8. Voigt, Tobias, Ulrich Katscher, and Olaf Doessel. "Quantitative conductivity and permittivity imaging of the human brain using electric properties tomography." *Magnetic Resonance in Medicine* 66.2 (2011): 456-466.

9. Bulumulla, Selaka Bandara, Seung-Kyun Lee, and Teck Beng Desmond Yeo. "Calculation of electrical properties from B1+ maps-a comparison of methods." *Brain* 68.65.7 (2012): 66-2.